



# SERVICE SLANTS

YOUR QUESTIONS OR COMMENTS ON "SERVICE SLANTS"  
ARE WELCOME AT ANY TIME

ISSUED BY WURLITZER SERVICE DEPT., NORTH TONAWANDA, N. Y.

SUBJECT: Part No. 62430 Transformer Hi Fi Output - 11 Wire  
Part No. 114259 Transformer Stereo Output - 11 Wire

The above subject 11 wire Transformers are replacements for the 12 wire Output Transformers carrying the same part numbers used in the Model 530 thru Model 538 Amplifiers.

The solid green wire of the 12 wire Transformer that was soldered to the "D" tap of the fader switch was eliminated by Engineering Request.

If these 11 wire Output Transformers are replacing a 12 wire Output Transformer--

1. Wire in the 11 wire Transformer following the same color code as the 12 wire Transformer removed except the Solid Green Wire that was soldered to the "D" tap of the fader switch is missing, leaving the "D" tap of the fader switch vacant.
2. Solder a jumper wire from this vacant "D" tap to the Green and Red wire on the "C" tap.
3. If there are any resistors in this fader switch circuit such as R-70 - R-71 or R-40 - R-41 (see Amplifier Schematic 530 thru 538) shunt them out with jumper wires.